

GSM WIRELESS FAX TERMINAL

FCT-343

- Support voice, fax and data
- With back-up battery inside



Technical Specification

- **Air Interface :**
GSM Phase I/GSM Phase II + compatible
- **GSM Frequency Band:** GSM900/1800MHz or
GSM850/1800/1900MHz
- **RF Transmit Power :** 2W (900 MHz), 1W (1800 MHz)
- **RF Sensitivity :** < -102 dBm
- **Electricity Power Supply :**
Input: AC90~260V/50Hz ; Output: DC12V/1.2A
- **Battery(Optional):** Ni-MH battery, 7.2V/1.2Ah
- **LED Indicators :**
Power /In Use/Fax/Run/Battery/Signal
- **Connectors :**
2 RJ-11 Interface : one for phone and the other for Fax
Serial port(RS232) interface for PC
SMA(male) antenna connector
DC power input jack
- **Antenna :**
2.5dbi Omni Antenna
Frequency band: 890~960MHz/1710~1880MHz

Main Features

- User-friendly installation; Plug & Play
- Support CLID, call restriction, call forward, call waiting, and auto PIN entry for SIM card
- LED indicators: Power/In Use/FaxRun/Battery/Signal
- SIM Card locking and Network locking
- Reverse Polarity signal support (12/16KHz optional)
- DTMF and pulse dialing
- Internal back-up Battery (optional)
- SMS & PC FAX(optional)
- RS-232 Connector for PC connection
- G3 analogue fax connection
- GPRS Data transmission(optional)

Environment

- **Operating temperature range :** -10°C to +50°C
- **Humidity :** 45% to 95%
- **Dimensions :** 420mm(L)x220mm(W)x70mm(H)
- **Weight :** 1.1Kgs (including antenna, battery and power adaptor)

MAXCOMM CO., LTD.

4F, NO. 283, COUNTY BLVD., SEC. 1, BAN CHIAO,
TAIPEI HSIEN 220, TAIWAN, R.O.C.

WWW.MAXCOMM.COM.TW

TEL: 886 2 2966 6648

FAX: 886 2 2969 8296

E-mail: info@maxcomm.com.tw